

connected to earth, even during the test). Clamps C.A 6412 and C.A 6415 can also be used to measure the leakage currents flowing to the ground. To further optimize your testing operations,

the C.A6415 model also has an alarm function (buzzer if threshold is exceeded) and a measurement logging function.

	Range (1)	Resolution	Accuracy <sup>(2)</sup>
Resistance measurement	0.10 to 1.00 $\Omega$ 1.0 to 50.0 $\Omega$ 50.0 to 100.0 $\Omega$ 100 to 200 $\Omega$ 200 to 400 $\Omega$ 400 to 600 $\Omega$ 600 to 1200 $\Omega$	$\begin{array}{c} 0.01 \; \Omega \\ 0.1 \; \Omega \\ 0.5 \; \Omega \\ 1 \; \Omega \\ 5 \; \Omega \\ 10 \; \Omega \\ \end{array}$	$\begin{array}{l} \pm (2 \% + 0.02 \ \Omega) \\ \pm (1.5 \ \% + 0.1 \ \Omega) \\ \pm (2.0 \ \% + 0.5 \ \Omega) \\ \pm (3.0 \ \% + 1 \ \Omega) \\ \pm (6.0 \ \% + 5 \ \Omega) \\ \pm (10 \ \% + 10 \ \Omega) \\ - \end{array}$
RMS current measurement (3)	1 to 300 mA 0.300 A to 3.000 A 3.00 A to 30.00 A	1 mA 1 mA 10 mA	± (2.5 % + 2 mA) ± (2.5 % + 2 mA) ± (2.5 % + 20 mA)

(1) Automatic range ch<mark>an</mark>ge In the reference conditions Additional function available on models C.A 6412 and C.A 6415



# **General specifications**

- Olamping diameter: 32 mm
- Temperature of use: -10°C to +55°C
- Storage temperature: -30°C to +70°C
- Relative humidity: 0 % to 75 % RH
- IP 30 as per EN 60529
- Dimensions : 235 x 100 x 55 mm
- Model C.A 6415:

Alarm threshold adjustable from 1  $\Omega$  to 199  $\Omega$ Memory capacity: 99 measurements.

## **Electrical specifications**

- Omplies with EN 61010-2-032
- Dual insulation, class 2
- 150 V, cat. III, pollution level 2
- Max. overcurrent: 100 A AC constant
- Measurement frequency: 2400 Hz
- Charge life: with 9 V alkaline battery (Cd/Ni battery accepted): 1500 thirty-second measurements



## To order


C.A 6410 ...... P01.1220.11 C.A 6412 ..... P01.1220.12 C.A 6415 ...... P01.1220.13

Each clamp-on earth resistance tester is delivered in a carrying case with one 9 V battery and a user's manual.



Calibration loop CL1 ......P01.1223.01

Your distributor



### Models C.A 6410, 6412 and 6415

Resistance measurement

**R** $\leq$ **1** $\Omega$  Resistance under 0.1  $\Omega$ 

Remaining battery charge life

Battery indicator

Automatic shutdown inhibited

**HOLD** Holding of display

• II) Buzzers active

**NOISE** Significant eddy currents

Jaws not closed properly

#### Models C.A 6412 and 6415

mA Current measurement

#### Model C<sub>4</sub>A 6415

♠ IBB Alarm function

**MEM** Recording in memory

Reading memory



Model C.A 6410

Model

C,A 6412

ON

Start  $\Omega$  / stop + autotest



ON

Start / stop + autotest

Ω Resistance measurement

Current measurement



Model C,A 6415

ON **OFF** 

Start / stop + autotest

Ω

Resistance measurement

Current measurement

**MEM** Recording of measurement

Alarm activation and adjustment